

## QT636

Quantec Interface Unit c/w Remote Socket



### Overview

Allows any device with a normally open or normally closed 6.35mm (1/4 inch) jack plug to be connected to Quantec.

Particularly suited for use with our NC805MD Portable Movement Detector (n/ooperation), QT644 Floor Pressure mat (n/ooperation), QT633 Bed Exit mat (n/coperation) or QT634 Chair ExitMat (n/c operation).

Must be wired as a slave to a QT602 or QT609 range addressable call point or QT630 dementia care controller.

When the device connected to the QT636 is operated a call will be generated on the Quantec call system as programmed.

Mounts on a standard UK 25mm single gang back box.

### Technical Specifications

|  |   |
|--|---|
| <b>Quiescent current</b>                 | 1mA.  |
| <b>Alarm current</b>                     | 1mA.  |
| <b>Connections</b>                       | N-; N+; L+; SW. Wired as a slave to a QT602 call point, QT609 call point or QT630 dementia care controller. |
| <b>Onboard 6.35mm Remote Jack Socket</b> | Yes, can be configured to accept a n/o or n/c jack plug.  |



|   |  |
|---|--|
| <b>Onboard Sounder</b>                  | No.  |
| <b>Onboard Infrared Receiver</b>        | No.  |
| <b>Product dimensions (mm)</b>          | 87 W x 87 H x 33 D mm. Can be mounted on a standard UK 25mm single gang flush or surface back box. |
| <b>Construction &amp; finish</b>        | Plastic.   |
| <b>IP Rating</b>                        | IP20.  |
| <b>Weight</b>                           | 68g  |
| <b>Operating conditions/temperature</b> | -5°C to +40°C. Max relative humidity: 95%.   |



T 01942 322744 E sales@c-tec.co.uk  
F 01942 829867 W www.c-tec.com



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom



T 01942 322744 E [sales@c-tec.co.uk](mailto:sales@c-tec.co.uk)  
F 01942 829867 W [www.c-tec.com](http://www.c-tec.com)



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom