

Hi-Fi stereo amplifier with Bluetooth player, USB/MP3 and FM radio

Features:

New amplifier with exclusive FONESTAR design, highly reliable and accurate reproduction.
 An exceptional finish with a brushed aluminium front and a high contrast and visible LCD display.
 Elegant and practical design, can be integrated into any setting, be it for home or professional use.
 Multiple playback options (Bluetooth, USB/MP3 and FM) and audio inputs make it very versatile and adaptable.
 Two microphone inputs allow it to be used as a karaoke player and for singing along to your favourite songs.
 Powerful sound without distortion that provides consistent playback of your music.
 Intuitive use.

Applications:

Hi-Fi amplifier for home or professional use: home, bars, pubs, restaurants, shops, schools, etc.

Technical data:

60 W + 60 W RMS



AS-6060

FEATURES	Hi-Fi stereo amplifier. Bluetooth 5.0 receiver. USB/MP3 player. FM radio. Echo microphone inputs. Digital audio input to connect to a TV. Aluminium panel. Remote control for player.
POWER	230 V AC, 350 W
RESPONSE	20-20,000 Hz
S/N RATIO	>85 dB
DISTORTION	Harmonic: < 0.5% at 1 kHz
INPUTS	3 stereo aux: DVD/AUX/CD, 2 x RCA, 17,000 Ohm 300 mV RMS 1 stereo aux, 3.5 mm jack, 15,000 Ohm 300 mV RMS on front panel 1 digital audio, TOSLINK and RCA 2 balanced mics, 6.3 mm jack, 900 Ohm 9 mV RMS

OUTPUTS	Speakers: Main L/R, 4-16 Ohm screw or banana terminals
PROTECTION	Temperature, short circuit and overload
DIMENSIONS	330 x 92 x 276 mm depth
WEIGHT	4.15 kg
ACCESSORIES	FM antenna cable Remote control